

DS26LS32AC/DS26LS32C/DS26LS32M/DS26LS33M Quad Differential Line Receivers

General Description

The DS26LS32 and DS26LS32A are quad differential line receivers designed to meet the RS-422, RS-423 and Federal Standards 1020 and 1030 for balanced and unbalanced digital data transmission.

The DS26LS32 and DS26LS32A have an input sensitivity of 200 mV over the input voltage range of $\pm 7V$ and the DS26LS33 have an input sensitivity of 500 mV over the input voltage range of $\pm 15V$.


The DS26LS32A differ in function from the popular DS26LS32 and DS26LS33 in that input pull-up and pull-down resistors are included which prevent output oscillation on unused channels.

Each version provides an enable and disable function common to all four receivers and features TRI-STATE ® outputs with 8 mA sink capability. Constructed using low power Schottky processing, these devices are available over the full military and commerical operating temperature ranges.

Features

- High differential or common-mode input voltage ranges of ±7V on the DS26LS32 and DS26LS32A and ±15V on the DS26LS33
- ±0.2V sensitivity over the input voltage range on the DS26LS32 and DS26LS32A, ±0.5V sensitivity on the DS26LS33
- DS26LS32 and DS26LS32A meet all requirements of RS-422 and RS-423
- 6k minimum input impedance
- 100 mV input hysteresis on the DS26LS32 and DS26LS32A, 200 mV on the DS26LS33
- Operation from a single 5V supply
- TRI-STATE outputs, with choice of complementary output enables for receiving directly onto a data bus


Logic Diagram



TRI-STATE® is a registered trademark of National Semiconductor Corporation.

Connection Diagrams


Dual-In-Line Package



Top View
Order Number DS26LS32CM, DS26LS32CN,
DS26LS32ACM, DS26LS32ACN, DS26LS33ACM
or DS26LS33ACN

See NS Package Number M16A or N16E
For Complete Military Product Specifications,
refer to the appropriate SMD or MDS.
Order Number DS26LS32MJ/883, DS26LS32MW/883,
DS26LS32ME/883, DS26LS33MW/883
See NS Package Number E20A, J16A or W16A

20-Lead Ceramic Leadless Chip Carrier



Truth Table

| ENABLE | ENABLE | Input | Output | | |
|--------|--------|-----------------------------------------|--------|--|--|
| 0 | 1 | X | Hi-Z | | |
| See | | V _{ID} ≥ V _{TH} (Max) | 1 | | |
| Note | Below | $V_{ID} \le V_{TH} (Min)$ | 0 | | |

Hi-Z = TRI-STATE®

Note: Input conditions may be any combination not defined for ENABLE and $\overline{\text{ENABLE}}$.

Absolute Maximum Ratings (Note 3)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications.

| Supply Voltage | 7V |
|--------------------------------------------|----------|
| Common-Mode Range | ±25V |
| Differential Input Voltage | ±25V |
| Enable Voltage | 7V |
| Output Sink Current | 50 mA |
| Maximum Power Dissipation (Note 1) at 25°C | |
| Cavity Package | 1433 mW |
| Molded Dip Package | 1362 mW |
| SO Package DS26LS32 | 1002 mW |
| DS26LS32A | 1051 mW |
| Storage Temperature Range | −65°C to |
| | +165°C |
| Lead Temperature (Soldering, 4 | |

Operating Conditions

| Min | Max | Units |
|------|--------------------|----------------------------------|
| | | |
| 4.5 | 5.5 | V |
| | | |
| 4.75 | 5.25 | V |
| | | |
| | | |
| | | |
| -55 | +125 | °C |
| | | |
| 0 | +70 | °C |
| | | |
| | | |
| | 4.5 4.75 –55 | 4.5 5.5 4.75 5.25 -55 +125 |

Note 1: Derate cavity package 9.6 mW/C above 25°C; derate molded DIP package 10.9 mW/C above 25°C.

Note 2: Derate SO Package 8.01 mW/°C for DS26LS32 8.41 mW/°C for DS26LS32A

seconds)

seconds)

Electrical Characteristics (Notes 4, 5, 6)

over the operating temperature range unless otherwise specified

| Symbol | Parameter | | Conditions | | | | Max | Units |
|-------------------|----------------------|---------------------------------------------------------|-----------------------------------------------|------------------------------------|------|-------|-------|-------|
| V _{TH} | Differential Input | $V_{OUT} = V_{OH}$ | DS26LS32, DS26LS32A, $-7V \le V_{CM} \le +7V$ | | | ±0.07 | 0.2 | V |
| | Voltage | or V _{OL} | DS26LS33, DS26 | LS33A, −15V ≤ V _{CM} +15V | -0.5 | ±0.14 | 0.5 | V |
| R _{IN} | Input Resistance | -15V ≤ V _{CM} ≤ | +15V (One Input A | 6.0 | 8.5 | | kΩ | |
| I _{IN} | Input Current (Under | $V_{IN} = 15V$, Other Input $-15V \le V_{IN} \le +15V$ | | | | | 2.3 | mA |
| | Test) | $V_{IN} = -15V, O$ | ther Input $-15V \le V$ | / _{IN} ≤ +15V | | | -2.8 | mA |
| V _{OH} | Output High Voltage | $V_{CC} = MIN, \Delta V$ | _{IN} = 1V, | Commercial | 2.7 | 4.2 | | V |
| | | $V_{\overline{\text{ENABLE}}} = 0.8$ | $I_{OH} = -440 \ \mu A$ | Military | 2.5 | 4.2 | | V |
| V _{OL} | Output Low Voltage | $V_{CC} = Min, \Delta V_{I}$ | _N = -1V, | I _{OL} = 4 mA | | | 0.4 | V |
| | | $V_{\overline{\text{ENABLE}}} = 0.8$ | / | I _{OL} = 8 mA | | | 0.45 | V |
| V _{IL} | Enable Low Voltage | | | | | | 0.8 | V |
| V _{IH} | Enable High Voltage | | | | 2.0 | | | V |
| V _I | Enable Clamp | V _{CC} = Min, I _{IN} = -18 mA | | | | | -1.5 | V |
| | Voltage | | | | | | | |
| Io | OFF-State (High | $V_{CC} = Max$ $V_{O} = 2.4V$ | | | | | 20 | μA |
| | Impedance) Output | | | V _O = 0.4V | | | -20 | μA |
| | Current | | | | | | | |
| I _{IL} | Enable Low Current | $V_{IN} = 0.4V$ | | | | | -0.36 | mA |
| I _{IH} | Enable High Current | $V_{IN} = 2.7V$ | $V_{IN} = 2.7V$ | | | | 20 | μA |
| I _{sc} | Output Short-Circuit | $V_O = 0V$, $V_{CC} = Max$, $\Delta V_{IN} = 1V$ | | | -15 | | -85 | mA |
| | Current | | | | | | | |
| I _{cc} | Power Supply | V _{CC} = Max, All | V _{IN} = GND, | DS26LS32, DS26LS32A | | 52 | 70 | mA |
| | Current | Outputs Disable | ed | DS26LS33, DS26LS33A | | 57 | 80 | mA |
| I ₁ | Input High Current | V _{IN} = 5.5V | | | | | 100 | μA |
| V _{HYST} | Input Hysteresis | $T_A = 25^{\circ}C, V_{CC}$ | ₅ = 5V, | DS26LS32, DS26S32A | | 100 | | mV |
| | | V _{CM} = 0V | | DS26LS33, DS26LS33A | | 200 | | mV |

260°C

Note 3: "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. They are not meant to imply that the device should be operated at these limits. The table of "Electrical Characteristics" provides conditions for actual device operation.

Note 4: All currents into device pins are shown as positive, all currents out of device pins are shown as negative, all voltages are referenced to ground, unless otherwise specified. All values shown as max or min are so classified on absolute value basis.

Note 5: All typical values are $V_{CC} = 5V$, $T_A = 25$ °C.

Note 6: Only one output at a time should be shorted.


3 www.national.com

Switching Characteristics V_{CC} = 5V, T_A = 25°C


| Symbol | Parameter | Conditions | DS26LS32/DS26LS33 | | | DS26L | DS26LS32A/DS26LS33A | | |
|------------------|------------------|---------------|-------------------|-----|-----|-------|---------------------|-----|----|
| | | | Min | Тур | Max | Min | Тур | Max | |
| t _{PLH} | Input to Output | $C_L = 15 pF$ | | 17 | 25 | | 23 | 35 | ns |
| t_{PHL} | | | | 17 | 25 | | 23 | 35 | ns |
| t_{LZ} | ENABLE to Output | $C_L = 5 pF$ | | 20 | 30 | | 15 | 30 | ns |
| t_{HZ} | | | | 15 | 22 | | 20 | 25 | ns |
| t _{ZL} | ENABLE to Output | $C_L = 15 pF$ | | 15 | 22 | | 14 | 22 | ns |
| t_{ZH} | | | | 15 | 22 | | 15 | 22 | ns |

AC Test Circuit and Switching Time Waveforms


Load Test Circuit for TRI-STATE® Outputs



Propagation Delay (Notes 7, 9)



Enable and Disable Times (Notes 8, 9)



Note 7: Diagram shown for ENABLE low.


Note 8: S1 and S2 of load circuit are closed except where shown.

Note 9: Pulse generator for all pulses: Rate = 1.0 MHz; $Z_O = 50\Omega$; $t_f \le 6$ ns; $t_f \le 6.0$ ns.


www.national.com

Typical Applications


Two-Wire Balanced Interface — RS-422




Single Wire with Driver Ground Reference—RS-423




Physical Dimensions inches (millimeters) unless otherwise noted



Ceramic Dual-In-Line Package (J) Order Number DS26LS32MJ/883 or DS26LS33MJ/883 **NS Package Number J16A**







Small Outline Package (M) Order Number DS26LS32CM or DS26LS32ACM **NS Package Number M16A**

www.national.com

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)





Molded Dual-In-Line Package (N)
Order Number DS26LS32CN or DS26LS32ACN
NS Package Number N16E



16 Lead Ceramic Flatpak (W)
Order Number DS26LS32MW/883 or DS26LS33MW/883
NS Package Number W16A

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)





20 Lead Ceramic Leadless Chip Carrier (E) Order Number DS26LS32ME/883 NS Package Number E20A

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

BANNED SUBSTANCE COMPLIANCE

National Semiconductor certifies that the products and packing materials meet the provisions of the Customer Products Stewardship Specification (CSP-9-111C2) and the Banned Substances and Materials of Interest Specification (CSP-9-111S2) and contain no "Banned Substances" as defined in CSP-9-111S2.



National Semiconductor Americas Customer Support Center

Email: new.feedback@nsc.com Tel: 1-800-272-9959

www.national.com

National Semiconductor
Europe Customer Support Center
Fax: +49 (0) 180-530 85 86
Email: europe support@nsc.com

Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 69 9508 6208
English Tel: +44 (0) 870 24 0 2171
Français Tel: +33 (0) 1 41 91 8790

National Semiconductor Asia Pacific Customer Support Center Email: ap.support@nsc.com National Semiconductor Japan Customer Support Center Fax: 81-3-5639-7507 Email: jpn.feedback@nsc.com Tel: 81-3-5639-7560

E20A (REV D)